

ADJ ENCORE PROFILE PRO WW

DMX TRAITS: FUNCTIONS & VALUES

Supports Software Versions: \geq 1.07					
Features subject to change without notice.					
MODE/CHANNEL				VALUE	FUNCTION
1CH	2CH	3CH	6CH		
1	1	1	1		Dimmer Intensity 8bit
				000-255	0 to 100%
	2	2	2	000-255	Dimmer Fine 16bit
					Shutter
				000-031	Shutter Closed (LEDs OFF)
				032-063	Shutter OPEN (LEDs ON)
				064-095	Strobe effect slow to fast
		3	3	096-127	Shutter OPEN (LEDs ON)
				128-159	Pulse effect in sequences
				160-191	Shutter OPEN (LEDs ON)
				192-223	Random strobe effect slow to fast
				224-255	Shutter OPEN (LEDs ON)
					Dim Modes
				000-020	Default to Unit Setting
				021-040	Standard
				041-060	Stage
				061-080	TV
				081-100	Architectural
				101-120	Theatre
				121-140	Stage 2
					Dimming Speed
				141	0.1Sec.
				142	0.2Sec.
				143	0.3Sec.
				144	0.4Sec.
				145	0.5Sec.
				146	0.6Sec.
			4	147	0.7Sec.
				148	0.8Sec.
				149	0.9Sec.
				150	1.0Sec.
				151	1.5Sec.
				152	2.0Sec.
				153	3.0Sec.
				154	4.0Sec.
				155	5.0Sec.
				156	6.0Sec.
				157	7.0Sec.
				158	8.0Sec.
				159	9.0Sec.
				160	10Sec.
				161-255	Default to Unit Setting
					Dim Curves
				000-020	Square
				021-040	Linear
				041-060	Inv. Squa
				061-080	S. Curve
			5	081-255	No Function

ADJ ENCORE PROFILE PRO WW

DMX TRAITS: FUNCTIONS & VALUES

Supports Software Versions: \geq 1.07					
Features subject to change without notice.					
MODE/CHANNEL				VALUE	FUNCTION
1CH	2CH	3CH	6CH		
					LED Refresh Rates
				000-028	1200 HZ LED Refresh Rate (Default)
				029-029	1080 Hz LED Refresh Rate
				030-030	1090 Hz LED Refresh Rate
				031-031	1100 Hz LED Refresh Rate
				032-032	1110 Hz LED Refresh Rate
				033-033	1120 Hz LED Refresh Rate
				034-034	1130 Hz LED Refresh Rate
				035-035	1140 Hz LED Refresh Rate
				036-036	1150 Hz LED Refresh Rate
				037-037	1160 Hz LED Refresh Rate
				038-038	1170 Hz LED Refresh Rate
				039-039	1180 Hz LED Refresh Rate
				040-040	1190 Hz LED Refresh Rate
				041-041	1210 Hz LED Refresh Rate
				042-042	1220 Hz LED Refresh Rate
				043-043	1230 Hz LED Refresh Rate
				044-044	1240 Hz LED Refresh Rate
				045-045	1250 Hz LED Refresh Rate
				046-046	1260 Hz LED Refresh Rate
				047-047	1270 Hz LED Refresh Rate
				048-048	1280 Hz LED Refresh Rate
				049-049	1290 Hz LED Refresh Rate
				050-050	1300 Hz LED Refresh Rate
				051-051	1310 Hz LED Refresh Rate
				052-052	1320 Hz LED Refresh Rate
			6	053-053	1330 Hz LED Refresh Rate
				054-054	1340 Hz LED Refresh Rate
				055-055	1350 Hz LED Refresh Rate
				056-056	1360 Hz LED Refresh Rate
				057-057	1370 Hz LED Refresh Rate
				058-058	1380 Hz LED Refresh Rate
				059-059	1390 Hz LED Refresh Rate
				060-060	1400 Hz LED Refresh Rate
				061-061	1410 Hz LED Refresh Rate
				062-062	1420 Hz LED Refresh Rate
				063-063	1430 Hz LED Refresh Rate
				064-064	1440 Hz LED Refresh Rate
				065-065	1450 Hz LED Refresh Rate
				066-066	1460 Hz LED Refresh Rate
				067-067	1470 Hz LED Refresh Rate
				068-068	1480 Hz LED Refresh Rate
				069-069	1490 Hz LED Refresh Rate
				070-070	1500 Hz LED Refresh Rate
				071-071	2500 Hz LED Refresh Rate
				072-072	4000 Hz LED Refresh Rate
				073-073	5000 Hz LED Refresh Rate
				074-074	6000 Hz LED Refresh Rate
				075-075	10K Hz LED Refresh Rate
				076-076	15K Hz LED Refresh Rate
				077-077	20K Hz LED Refresh Rate
				078-078	25K Hz LED Refresh Rate
				079-079	Disable LED Refresh Rate
				080-255	No Function