

ELIMINATOR STRYKER MAX - DMX TRAITS

CHANNEL		DMX VALUES	FUNCTION
20Ch	26Ch		
1	1	000 - 255	Pan , 8-bit, 0° - 540°
	2	000 - 255	Pan Fine , 16-bit
2	3	000 - 255	Tilt , 8-bit, 0° - 190°
	4	000 - 255	Tilt Fine , 16-bit
3	5	000 - 255	Red
4	6	000 - 255	Green
5	7	000 - 255	Blue
6	8	000 - 255	White
	9	000 - 255	Hue
	10	000 - 255	Saturation
	11		CCT Presets
		000	No Function
		001 - 027	2800K
		028 - 055	3200K
		056 - 083	3600K
		084 - 111	4500K
		112 - 139	5000K
		140 - 167	5600K
		168 - 195	6200K
		196 - 223	6800K
		224 - 251	7500K
		252 - 255	8500K
7	12		Color Macros
		000	Off
		001 - 255	Color Macros, Macro 1 - Macro 255
8	13		Effect
		000	Effect Off
		001 - 100	Wave
		101 - 200	Dream
	201 - 255	Color Chase	
9	14	000 - 255	Glory Red
10	15	000 - 255	Glory Green
11	16	000 - 255	Glory Blue
12	17	000 - 255	Glory Dimmer
13	18		Glory Effect
		000 - 015	Glory Effect close
		016 - 035	Glory single LED effect
		036 - 055	Glory 3pcs LED effect
		056 - 075	Glory 6pcs LED effect
		076 - 095	Glory 12pcs LED effect
096 - 115	Glory 3pcs LED-4 modules effect		

ELIMINATOR STRYKER MAX - DMX TRAITS

CHANNEL		DMX VALUES	FUNCTION
20Ch	26Ch		
13	18		Glory Effect (continued)
		116 - 135	Glory 6pcs LED-4 modules effect
		136 - 155	Glory 4 modules effect
		156 - 175	Glory loop fill effect
		176 - 195	RGB 3 colors rainbow effect
		196 - 215	RGB 3 colors effect
		216 - 235	Glory rainbow effect
		236 - 255	Glory segment effect
14	19	000 - 255	Glory Speed
15	20	000 - 255	Zoom , minimum to maximum
16	21		Inner Rotate
		000 - 127	Positions
		128 - 190	Clockwise, fast to slow
		191 - 192	Stop
		193 - 255	Counter-clockwise, slow to fast
17	22		Shutter
		000 - 003	Off
		004 - 127	Strobe, slow to fast
		128 - 191	Pulse Strobe, slow to fast
		192 - 251	Random Strobe, slow to fast
		252 - 255	Open
18	23	000 - 255	Dimmer , 0-100%
	24	000 - 255	Dimmer Fine , 16-bit
19	25	000 - 255	Pan/Tilt Speed , fast to slow
20	26		Reset
		000 - 021	Off
		022 - 025	No Function
		026 - 076	Reset Effect (hold 3 sec)
		077 - 128	Reset Pan/Tilt Motor (hold 3 sec)
		129 - 255	Reset All (hold 3 sec)