

ADJ MIRAGE PAR H IP - DMX TRAITS

CHANNEL						DMX VALUES	FUNCTION
5Ch	6Ch	9Ch A	9Ch B	15 Ch	17 Ch		
	1	1		1	1	0 - 255	Red 0 - 100%
	2	2		2	2	0 - 255	Green 0 - 100%
	3	3		3	3	0 - 255	Blue 0 - 100%
	4	4		4	4	0 - 255	Amber 0 - 100%
	5	5		5	5	0 - 255	Lime 0 - 100%
	6	6		6	6	0 - 255	UV 0 - 100%
		7	1	7	7	0 - 255	Colors Macros Refer to Color Macros Chart
1		8	2	8	8	0 - 255	Color Temperature 2300K - 9900K Linear
2		9	3	9	9	0 - 22	White Color Temperature Presets Open
						23 - 99	White Color Temperature Presets, refer to Color Temperature Chart
						100 - 255	No Function
3			4	10	10	0 - 31	Shutter LEDs Off
						32 - 63	LEDs On
						64 - 95	Strobe effect, slow to fast
						96 - 127	LEDs On
						128 - 159	Pulse Effect in sequences
						160 - 191	LEDs On
						192 - 223	Random Strobe Effect, slow to fast
						224 - 255	LEDs On
4			5	11	11	0 - 255	Dimmer Intensity, 0 - 100%
5			6	12	12	0 - 255	Dimmer Fine Dimmer fine adjustment

ADJ MIRAGE PAR H IP - DMX TRAITS

CHANNEL						DMX VALUES	FUNCTION
5Ch	6Ch	9Ch A	9Ch B	15 Ch	17 Ch		
			7	13	13		Internal Programs
						0 - 10	Off
						11 - 26	Auto Program 1
						27 - 43	Auto Program 2
						44 - 60	Auto Program 3
						61 - 76	Auto Program 4
						77 - 93	Auto Program 5
						94 - 110	Auto Program 6
						111 - 126	Auto Program 7
						127 - 143	Auto Program 8
						144 - 160	Auto Program 9
						161 - 176	Auto Program 10
						177 - 193	Auto Program 11
						194 - 210	Auto Program 12
						211 - 226	Auto Program 13
						227 - 255	No Function
			8	14	14		Programs Speed
						0 - 255	Slow to fast
			9	15	15		Program Fade
						0 - 255	Least to most
							Dim Mode
						0 - 20	Default to unit setting
						21 - 40	Standard
						41 - 60	Stage
						61 - 80	TV
						81 - 100	Architectural
						101 - 120	Theatre
						121 - 140	Stage 2
							Dim Speed
					16	141	0.1 s
						142	0.2 s
						143	0.3 s
						144	0.4 s
						145	0.5 s
						146	0.6 s
						147	0.7 s
						148	0.8 s
						149	0.9 s
						150	1.0 s
						151	1.5 s
						152	2.0 s

ADJ MIRAGE PAR H IP - DMX TRAITS

CHANNEL						DMX VALUES	FUNCTION
5Ch	6Ch	9Ch A	9Ch B	15 Ch	17 Ch		
					16		Dim Speed (continued)
						153	3.0 s
						154	4.0 s
						155	5.0 s
						156	6.0 s
						157	7.0 s
						158	8.0 s
						159	9.0 s
						160	10.0 s
						161 - 255	Default to unit setting
						17	
					0 - 20		Square
					21 - 40		Linear
					41 - 60		Inv Squa
					61 - 80		S Curve
					81 - 255		No Function