

DMX TRAITS: CHANNEL FUNCTIONS & VALUES (6/8/14/14/17/56/60/66/69 DMX Channels)

6CH	8CH	14Ch	14CH	17CH	56CH	60CH	66CH	69CH	Values	Functions
	1	1	1	1					000-255	White Main Pixels 1-14 0% - 100%
	2	2		2					000-255	Red Background Color 1-14 0% - 100%
	3	3		3					000-255	Green Background Color 1-14 0% - 100%
	4	4		4					000-255	Blue Background Color 1-14 0% - 100%
					1	1	1	1	000-255	White Main Pixel 1 0% - 100%
					2	2	2	2	000-255	White Main Pixel 2 0% - 100%
					3	3	3	3	000-255	White Main Pixel 3 0% - 100%
					4	4	4	4	000-255	White Main Pixel 4 0% - 100%
...
					14	14	14	14	000-255	White Main Pixel 14 0% - 100%
					15	15	15	15	000-255	Red Background Color 1 0% - 100%
					16	16	16	16	000-255	Green Background Color 1 0% - 100%
					17	17	17	17	000-255	Blue Background Color 1 0% - 100%
...
					54	54	54	54	000-255	Red Background Color 14 0% - 100%
					55	55	55	55	000-255	Green Background Color 14 0% - 100%
					56	56	56	56	000-255	Blue Background Color 14 0% - 100%
			2	5				57	000-255	Background Color 1-14, COLOR TEMPERATURE LINEAR 2700-6000K
									000-031	No Function
									000-255	2700K-6000K
								58		Background Color 1-14, COLOR TEMPERATURE PRESETS
									000-031	No Function
			3	6					032-255	2700K
									077-121	3200K
									122-166	4000K
									167-211	5600K
									212-255	6000K
			4	7				59	000-255	Background Pixel 1-14, 64 Color Macros (See Color Macros Chart)
								60		White Pixel 1-14 Shutter
									000-031	Shutter Closed (LEDs OFF)
									032-063	Shutter OPEN (LEDs ON)
									064-095	Strobe effect slow to fast
									096-127	Shutter OPEN (LEDs ON)
									128-159	Pulse effect in sequences
									160-191	Shutter OPEN (LEDs ON)
									192-223	Random strobe effect slow to fast
									224-255	Open
	6	6	6	9		58	58	61	000-255	White Pixel 1-14 Dimmer

DMX TRAITS: CHANNEL FUNCTIONS & VALUES (6/8/14/14/17/56/60/66/69 DMX Channels)

6CH	8CH	14Ch	14CH	17CH	56CH	60CH	66CH	69CH	Values	Functions
										Background Color 1-14 Shutter
									000-031	Shutter Closed (LEDs OFF)
									032-063	Shutter OPEN (LEDs ON)
	7	7	7	10		59	59	62	064-095	Strobe effect slow to fast
									096-127	Shutter OPEN (LEDs ON)
									128-159	Pulse effect in sequences
									160-191	Shutter OPEN (LEDs ON)
									192-223	Random strobe effect slow to fast
									224-255	Open
	8	8	8	11		60	60	63	000-255	Background Color 1-14 Dimmer
										White LEDs Auto
									0-14	No Function
									15-29	Auto 1
									30-44	Auto 2
									45-59	Auto 3
									60-74	Auto 4
									75-89	Auto 5
									90-104	Auto 6
1			9	12			61	64	105-119	Auto 7
									120-134	Auto 8
									135-149	Auto 9
									150-164	Auto 10
									165-179	Auto 11
									180-194	Auto 12
									195-209	Auto 13
									210-224	Auto 14
									225-239	Auto 15
									240-255	Sound
2		10	10	13			62	65	000-255	White LEDs Auto Speed (Slow to Fast)
3		11	11	14			63	66	000-255	White LEDs Auto Fade
										RGB LED's Auto
									0-14	No Function
									15-29	RGB 1
									30-44	RGB 2
									45-59	RGB 3
									60-74	RGB 4
									75-89	RGB 5
									90-104	RGB 6
4		12	12	15			64	67	105-119	RGB 7
									120-134	RGB 8
									135-149	RGB 9
									150-164	RGB 10
									165-179	RGB 11
									180-194	RGB 12
									195-209	RGB 13
									210-224	RGB 14
									225-239	RGB 15
									240-255	RGB 16
5		13	13	16			65	68	000-255	RGB LED's Auto Speed (Slow to Fast)
6		14	14	17			66	69	000-255	RGB LED's Auto Fade