

ELIMINATOR IKON PROFILE PLUS - DMX TRAITS

| CHANNEL MODE | | DMX VALUES | FUNCTION |
|--------------|-----|------------|-----------------------------|
| 3Ch | 4Ch | | |
| 1 | 1 | | <i>Strobe</i> |
| | | 000 - 031 | LED Off |
| | | 032 - 063 | LED On |
| | | 064 - 095 | Strobe, slow to fast |
| | | 096 - 127 | LED On |
| | | 128 - 159 | Strobe Pulse, slow to fast |
| | | 160 - 191 | LED On |
| | | 192 - 223 | Random Strobe, slow to fast |
| | | 224 - 255 | LED On |
| 2 | 2 | 000 - 255 | <i>Dimmer</i> |
| | 3 | 000 - 255 | <i>Dimmer Fine</i> |
| 3 | 4 | | <i>Dim Curves</i> |
| | | 000 - 020 | Standard |
| | | 021 - 040 | Stage |
| | | 041 - 060 | TV |
| | | 061 - 080 | Architectural |
| | | 081 - 100 | Theatre |
| | | 101 - 120 | Stage 2 |
| | | 121 - 255 | Default to Unit Setting |