

# ELIMINATOR MEGA HEX L PAR - DMX TRAITS

CHANNEL							DMX VALUES	FUNCTION				
6Ch	8Ch	9Ch	12Ch	14Ch	15Ch	17Ch						
1	1	1	1	1	1	1	000 - 255	<b>All Red</b> , 0% to 100%				
2	2	2	2	2	2	2	000 - 255	<b>All Green</b> , 0% to 100%				
3	3	3	3	3	3	3	000 - 255	<b>All Blue</b> , 0% to 100%				
4	4	4	4	4	4	4	000 - 255	<b>All Lime</b> , 0% to 100%				
5	5	5	5	5	5	5	000 - 255	<b>All Amber</b> , 0% to 100%				
6	6	6	6	6	6	6	000 - 255	<b>All UV</b> , 0% to 100%				
			7		7	7	000 - 255	<b>Color Macros</b> , see <b>Color Macros Chart</b> section of this manual				
			8		8	8	000 - 255	<b>Color Temperature</b> , 2300K - 9900K Linear				
			9		9	9		<b>White Color Temperature Presets</b>				
									000 - 022	Open		
									023 - 099	See <b>White Color Temperature Chart</b> section of this manual		
									100 - 255	No function		
	7	7	10	7	10	10		<b>Shutter, Strobe</b>				
							000 - 031	LEDs Off				
							032 - 063	LEDs On				
							064 - 095	Strobe Effect, slow to fast				
							096 - 127	LEDs On				
							128 - 159	Pulse Effect in Sequences				
							160 - 191	LEDs On				
							192 - 223	Random Strobe Effect, slow to fast				
						224 - 255	LEDs On					
	8	8	11	8	11	11	000 - 255	<b>Dimmer Intensity</b> , 0% to 100%				
		9	12	9	12	12	000 - 255	<b>Dimmer Fine</b>				
			10	13	13	13		<b>Auto Programs</b>				
											000 - 010	Off
											011 - 026	Auto Program 1
											027 - 043	Auto Program 2
											044 - 060	Auto Program 3
											061 - 076	Auto Program 4
											077 - 093	Auto Program 5
											094 - 110	Auto Program 6
											111 - 126	Auto Program 7
											127 - 143	Auto Program 8
											144 - 160	Auto Program 9
											161 - 176	Auto Program 10
											177 - 193	Auto Program 11
											194 - 210	Auto Program 12
							211 - 226	Auto Program 13				
							227 - 255	No function				
			11	14	14	14	000 - 255	<b>Auto Programs Speed</b> , slow to fast				

CONTINUED ON NEXT PAGE

# ELIMINATOR MEGA HEX L PAR - DMX TRAITS

CHANNEL							DMX VALUE	FUNCTION
6Ch	8Ch	9Ch	12Ch	14Ch	15Ch	17Ch		
				12	15	15	000 - 255	<b>Auto Programs Fade</b> , least to most
				13		16		<b>Dim Mode</b>
							000 - 020	Default to unit setting
							021 - 040	Standard
							041 - 060	Stage
							061 - 080	TV
							081 - 100	Architectural
							101 - 120	Theatre
							121 - 140	Stage 2
								<b>Dim Speed</b>
							141	0.1s
							142	0.2s
							143	0.3s
							144	0.4s
							145	0.5s
							146	0.6s
							147	0.7s
							148	0.8s
							149	0.9s
							150	1.0s
							151	1.5s
				152	2.0s			
				153	3.0s			
				154	4.0s			
				155	5.0s			
				156	6.0s			
				157	7.0s			
				158	8.0s			
				159	9.0s			
				160	10.0s			
					161 - 255	Default to unit setting		
				14		17		<b>Dim Curves</b>
							000 - 020	Square
							021 - 040	Linear
							041 - 060	Inv. Squa
							061 - 080	S. Curve
					081 - 255	No Function		