

# ELIMINATOR MEGA WASH 24 - DMX TRAITS

CHANNEL				DMX VALUES	FUNCTION
3CH	6CH	10CH	40CH		
	1	1		0 - 255	<b>Red Color</b> , 0% to 100%
	2	2		0 - 255	<b>Green Color</b> , 0% to 100%
	3	3		0 - 255	<b>Blue Color</b> , 0% to 100%
	4	4		0 - 255	<b>White Color</b> , 0% to 100%
	5	5		0 - 255	<b>Amber Color</b> , 0% to 100%
	6	6		0 - 255	<b>UV Color</b> , 0% to 100%
1		8	1		<b>Auto Mode / Sound Control Mode</b>
				0 - 9	No function
				10 - 17	Auto Mode 1
				18 - 25	Auto Mode 2
				26 - 33	Auto Mode 3
				34 - 41	Auto Mode 4
				42 - 49	Auto Mode 5
				50 - 57	Auto Mode 6
				58 - 65	Auto Mode 7
				66 - 73	Auto Mode 8
				74 - 81	Auto Mode 9
				82 - 89	Auto Mode 10
				90 - 97	Auto Mode 11
				98 - 105	Auto Mode 12
				106 - 113	Auto Mode 13
				114 - 121	Auto Mode 14
				122 - 129	Auto Mode 15
				130 - 137	Auto Mode 16
				138 - 145	Auto Mode 17
				146 - 153	Auto Mode 1 - 17 Cycling
				154 - 161	Sound Control Mode 1
162 - 169	Sound Control Mode 2				
170 - 177	Sound Control Mode 3				
178 - 185	Sound Control Mode 4				
186 - 193	Sound Control Mode 5				
194 - 201	Sound Control Mode 6				
202 - 209	Sound Control Mode 7				
210 - 217	Sound Control Mode 8				

CONTINUED ON NEXT PAGE

# ELIMINATOR MEGA WASH 24 - DMX TRAITS

CHANNEL				DMX VALUES	FUNCTION
3CH	6CH	10CH	40CH		
1		8	1		<b>Auto Mode / Sound Control Mode (continued)</b>
				218 - 225	Sound Control Mode 9
				226 - 233	Sound Control Mode 10
				234 - 241	Sound Control Mode 11
				242 - 255	Sound Control Mode 1 - 11 Cycling
2		9	2	0 - 255	<b>Auto Mode Speed</b> , slow to fast
3		10	3	0 - 255	<b>Master Dimming</b> , 0% to 100%
		7	4		<b>Strobing</b>
				0 - 9	Full On
				10 - 255	Strobe Speed, slow to fast
			5	0 - 255	<b>Red Zone 1</b> , 0% to 100%
			6	0 - 255	<b>Green Zone 1</b> , 0% to 100%
			7	0 - 255	<b>Blue Zone 1</b> , 0% to 100%
			8	0 - 255	<b>White Zone 1</b> , 0% to 100%
			9	0 - 255	<b>Amber Zone 1</b> , 0% to 100%
			10	0 - 255	<b>UV Zone 1</b> , 0% to 100%
			11	0 - 255	<b>Red Zone 2</b> , 0% to 100%
			12	0 - 255	<b>Green Zone 2</b> , 0% to 100%
			13	0 - 255	<b>Blue Zone 2</b> , 0% to 100%
			14	0 - 255	<b>White Zone 2</b> , 0% to 100%
			15	0 - 255	<b>Amber Zone 2</b> , 0% to 100%
			16	0 - 255	<b>UV Zone 2</b> , 0% to 100%
			17	0 - 255	<b>Red Zone 3</b> , 0% to 100%
			18	0 - 255	<b>Green Zone 3</b> , 0% to 100%
			19	0 - 255	<b>Blue Zone 3</b> , 0% to 100%
			20	0 - 255	<b>White Zone 3</b> , 0% to 100%
			21	0 - 255	<b>Amber Zone 3</b> , 0% to 100%
			22	0 - 255	<b>UV Zone 3</b> , 0% to 100%
			23	0 - 255	<b>Red Zone 4</b> , 0% to 100%
			24	0 - 255	<b>Green Zone 4</b> , 0% to 100%
			25	0 - 255	<b>Blue Zone 4</b> , 0% to 100%
			26	0 - 255	<b>White Zone 4</b> , 0% to 100%
			27	0 - 255	<b>Amber Zone 4</b> , 0% to 100%
			28	0 - 255	<b>UV Zone 4</b> , 0% to 100%
			29	0 - 255	<b>Red Zone 5</b> , 0% to 100%
			30	0 - 255	<b>Green Zone 5</b> , 0% to 100%
			31	0 - 255	<b>Blue Zone 5</b> , 0% to 100%
			32	0 - 255	<b>White Zone 5</b> , 0% to 100%

CONTINUED ON NEXT PAGE

# ELIMINATOR MEGA WASH 24 - DMX TRAITS

CHANNEL				DMX VALUES	FUNCTION
3CH	6CH	10CH	40CH		
			33	0 - 255	<b><i>Amber Zone 5</i></b> , 0% to 100%
			34	0 - 255	<b><i>UV Zone 5</i></b> , 0% to 100%
			35	0 - 255	<b><i>Red Zone 6</i></b> , 0% to 100%
			36	0 - 255	<b><i>Green Zone 6</i></b> , 0% to 100%
			37	0 - 255	<b><i>Blue Zone 6</i></b> , 0% to 100%
			38	0 - 255	<b><i>White Zone 6</i></b> , 0% to 100%
			39	0 - 255	<b><i>Amber Zone 6</i></b> , 0% to 100%
			40	0 - 255	<b><i>UV Zone 6</i></b> , 0% to 100%