

ADJ JOLT PANEL FXIP - DMX TRAITS

CHANNEL														DMX VALUES	FUNCTION
6 CH	9 CH	13 CH	18 CH	20 CH	36 CH	41 CH	43 CH	51 CH	81 CH	83 CH	126 CH	141 CH	143 CH		
					1	1	1	1	1	1	1	1	1	000-255	Red 1
					2	2	2	2	2	2	2	2	2	000-255	Green 1
					3	3	3	3	3	3	3	3	3	000-255	Blue 1
					4	4	4	4	4	4	4	4	4	000-255	Red 2
					5	5	5	5	5	5	5	5	5	000-255	Green 2
					6	6	6	6	6	6	6	6	6	000-255	Blue 2
					7	7	7	7	7	7	7	7	7	000-255	Red 3
					8	8	8	8	8	8	8	8	8	000-255	Green 3
					9	9	9	9	9	9	9	9	9	000-255	Blue 3
					10	10	10	10	10	10	10	10	10	000-255	Red 4
					11	11	11	11	11	11	11	11	11	000-255	Green 4
					12	12	12	12	12	12	12	12	12	000-255	Blue 4
					13	13	13	13	13	13	13	13	13	000-255	Red 5
					14	14	14	14	14	14	14	14	14	000-255	Green 5
					15	15	15	15	15	15	15	15	15	000-255	Blue 5
					16	16	16	16	16	16	16	16	16	000-255	Red 6
					17	17	17	17	17	17	17	17	17	000-255	Green 6
					18	18	18	18	18	18	18	18	18	000-255	Blue 6
					19	19	19	19	19	19	19	19	19	000-255	Red 7
					20	20	20	20	20	20	20	20	20	000-255	Green 7
					21	21	21	21	21	21	21	21	21	000-255	Blue 7
					22	22	22	22	22	22	22	22	22	000-255	Red 8
					23	23	23	23	23	23	23	23	23	000-255	Green 8
					24	24	24	24	24	24	24	24	24	000-255	Blue 8
								25	25	25	25	25	25	000-255	Red 9
								26	26	26	26	26	26	000-255	Green 9
								27	27	27	27	27	27	000-255	Blue 9
								28	28	28	28	28	28	000-255	Red 10
								29	29	29	29	29	29	000-255	Green 10
								30	30	30	30	30	30	000-255	Blue 10
								31	31	31	31	31	31	000-255	Red 11
								32	32	32	32	32	32	000-255	Green 11
								33	33	33	33	33	33	000-255	Blue 11
								34	34	34	34	34	34	000-255	Red 12
								35	35	35	35	35	35	000-255	Green 12
								36	36	36	36	36	36	000-255	Blue 12
								37	37	37	37	37	37	000-255	Red 13
								38	38	38	38	38	38	000-255	Green 13
								39	39	39	39	39	39	000-255	Blue 13
								40	40	40	40	40	40	000-255	Red 14

ADJ JOLT PANEL FXIP - DMX TRAITS

CHANNEL														DMX VALUES	FUNCTION
6 CH	9 CH	13 CH	18 CH	20 CH	36 CH	41 CH	43 CH	51 CH	81 CH	83 CH	126 CH	141 CH	143 CH		
									41	41	41	41	41	000-255	Green 14
									42	42	42	42	42	000-255	Blue 14
									43	43	43	43	43	000-255	Red 15
									44	44	44	44	44	000-255	Green 15
									45	45	45	45	45	000-255	Blue 15
									46	46	46	46	46	000-255	Red 16
									47	47	47	47	47	000-255	Green 16
									48	48	48	48	48	000-255	Blue 16
									49	49	49	49	49	000-255	Red 17
									50	50	50	50	50	000-255	Green 17
									51	51	51	51	51	000-255	Blue 17
									52	52	52	52	52	000-255	Red 18
									53	53	53	53	53	000-255	Green 18
									54	54	54	54	54	000-255	Blue 18
									55	55	55	55	55	000-255	Red 19
									56	56	56	56	56	000-255	Green 19
									57	57	57	57	57	000-255	Blue 19
									58	58	58	58	58	000-255	Red 20
									59	59	59	59	59	000-255	Green 20
									60	60	60	60	60	000-255	Blue 20
											61	61	61	000-255	Red 21
											62	62	62	000-255	Green 21
											63	63	63	000-255	Blue 21
											64	64	64	000-255	Red 22
											65	65	65	000-255	Green 22
											66	66	66	000-255	Blue 22
											67	67	67	000-255	Red 23
											68	68	68	000-255	Green 23
											69	69	69	000-255	Blue 23
											70	70	70	000-255	Red 24
											71	71	71	000-255	Green 24
											72	72	72	000-255	Blue 24
											73	73	73	000-255	Red 25
											74	74	74	000-255	Green 25
											75	75	75	000-255	Blue 25
											76	76	76	000-255	Red 26
											77	77	77	000-255	Green 26
											78	78	78	000-255	Blue 26
											79	79	79	000-255	Red 27
											80	80	80	000-255	Green 27

ADJ JOLT PANEL FXIP - DMX TRAITS

CHANNEL													DMX VALUES	FUNCTION		
6 CH	9 CH	13 CH	18 CH	20 CH	36 CH	41 CH	43 CH	51 CH	81 CH	83 CH	126 CH	141 CH			143 CH	
												81	81	81	000-255	Blue 27
												82	82	82	000-255	Red 28
												83	83	83	000-255	Green 28
												84	84	84	000-255	Blue 28
												85	85	85	000-255	Red 29
												86	86	86	000-255	Green 29
												87	87	87	000-255	Blue 29
												88	88	88	000-255	Red 30
												89	89	89	000-255	Green 30
												90	90	90	000-255	Blue 30
												91	91	91	000-255	Red 31
												92	92	92	000-255	Green 31
												93	93	93	000-255	Blue 31
												94	94	94	000-255	Red 32
												95	95	95	000-255	Green 32
												96	96	96	000-255	Blue 32
												97	97	97	000-255	Red 33
												98	98	98	000-255	Green 33
												99	99	99	000-255	Blue 33
												100	100	100	000-255	Red 34
												101	101	101	000-255	Green 34
												102	102	102	000-255	Blue 34
												103	103	103	000-255	Red 35
												104	104	104	000-255	Green 35
												105	105	105	000-255	Blue 35
												106	106	106	000-255	Red 36
												107	107	107	000-255	Green 36
												108	108	108	000-255	Blue 36
												109	109	109	000-255	Red 37
												110	110	110	000-255	Green 37
												111	111	111	000-255	Blue 37
												112	112	112	000-255	Red 38
												113	113	113	000-255	Green 38
												114	114	114	000-255	Blue 38
												115	115	115	000-255	Red 39
												116	116	116	000-255	Green 39
												117	117	117	000-255	Blue 39
												118	118	118	000-255	Red 40
												119	119	119	000-255	Green 40
												120	120	120	000-255	Blue 40

ADJ JOLT PANEL FXIP - DMX TRAITS

CHANNEL														DMX VALUES	FUNCTION
6 CH	9 CH	13 CH	18 CH	20 CH	36 CH	41 CH	43 CH	51 CH	81 CH	83 CH	126 CH	141 CH	143 CH		
				4			25			61			121		CT Presets
														000-022	Open
														023-089	CTO 2300K - 8900K
														090-255	9000K
				5			26			62			122	000-255	Green Shift
1	1	1	1	1											Outer Red: 0 to 100%
2	2	2	2	2											Outer Green: 0 to 100%
3	3	3	3	3											Outer Blue: 0 to 100%
		5	4	6		25	27	31	61	63		121	123	000-255	Outer Color Macros
			5	7	25	26	28	32	62	64		122	124	000-255	Outer Dimmer: 0 to 100%
			6	8	26	27	29	33	63	65		123	125	000-255	Outer Dimmer Fine: 0 to 100%
															Outer Strobe Effect
														000-002	Open
														003-005	Strobe
		8	7	9	27	28	30	34	64	66		124	126	006-500	Ramp up
														051-100	Ramp down
														101-150	Ramp up-down
														151-200	Lightning
														201-255	Random
		9	8	10	28	29	31	35	65	67		125	127	000-255	Outer Strobe Rate, Speed: Slow to Fast
		10	9	11	29	30	32	36	66	68		126	128	000-255	Outer Strobe Duration, Duration Slow to Fast
															Outer Program Macro
														000-005	No function
														006-015	Macro1
														016-025	Macro2
														026-035	Macro3
														036-045	Macro4
														046-055	Macro5
														056-065	Macro6
														066-075	Macro7
		11	10	12		31	33	37	67	69		127	129	076-085	Macro8
														086-095	Macro9
														096-105	Macro10
														106-115	Macro11
														116-125	Macro12
														126-135	Macro13
														136-145	Macro14
														146-155	Macro15
														156-165	Macro16
														166-175	Macro17
														176-185	Macro18
														186-195	Macro19

ADJ JOLT PANEL FXIP - DMX TRAITS

CHANNEL														DMX VALUES	FUNCTION	
6 CH	9 CH	13 CH	18 CH	20 CH	36 CH	41 CH	43 CH	51 CH	81 CH	83 CH	126 CH	141 CH	143 CH			
																Outer Program Macro (continued)
		11	10	12		31	33	37	67	69		127	129	196-205	Macro20	
														206-215	Macro21	
														216-225	Macro22	
														226-235	Macro23	
														236-245	Macro24	
														246-255	Macro25	
			11	13		32	34	38	68	70		128	130	0-255	Outer Program Macro Speed	
								39	69	71	121	129	131	000-255	White 1	
								40	70	72	122	130	132	000-255	White 2	
								41	71	73	123	131	133	000-255	White 3	
								42	72	74	124	132	134	000-255	White 4	
								43	73	75	125	133	135	000-255	White 5	
								44	74	76	126	134	136	000-255	White 6	
4	4	4													Inner White: 0 to 100%	
					30	33	35							000-255	Inner White Group 1	
					31	34	36							000-255	Inner White Group 2	
			12	14	32	35	37	45	75	77		135	137	000-255	Inner Dimmer: 0 to 100%	
			13	15	33	36	38	46	76	78		136	138	000-255	Inner Dimmer Fine: 0 to 100%	
															Inner Strobe Effect	
														000-002	Open	
														003-005	Strobe	
			14	16	34	37	39	47	77	79		137	13-	006-050	Ramp up	
														051-100	Ramp down	
														101-150	Ramp up-down	
														151-200	Lightning	
														201-255	Random	
			15	17	35	38	40	48	78	80		138	140	000-255	Inner Strobe Rate, Speed: Slow to Fast	
			16	18	36	39	41	49	79	81		139	141	000-255	Inner Strobe Duration, Duration Slow to Fast	
															Inner Program Macro	
														000-005	No function	
														006-033	Macro1	
														034-060	Macro2	
														061-088	Macro3	
		12	17	19		40	42	50	80	82		140	142	089-116	Macro4	
														117-144	Macro5	
														145-172	Macro6	
														173-200	Macro7	
														201-228	Macro8	
														229-255	Macro9	

ADJ JOLT PANEL FXIP - DMX TRAITS

CHANNEL														DMX VALUES	FUNCTION
6 CH	9 CH	13 CH	18 CH	20 CH	36 CH	41 CH	43 CH	51 CH	81 CH	83 CH	126 CH	141 CH	143 CH		
			18	20		41	43	51	81	83		141	143	000-255	Inner Program Macro Speed
		13												000-255	In/Out Program Macro Speed, Slow to Fast
5	5	6												000-255	Dimmer: 0 to 100%
6	6	7												000-255	Dimmer Fine: 0 to 100%
															Strobe Effect
														000-002	Open
														003-005	Strobe
														006-050	Ramp up
														051-100	Ramp down
														101-150	Ramp up-down
														151-200	Lightning
														201-255	Random
	8													000-255	Strobe Rate, Speed: Slow to Fast
	9													000-255	Strobe Duration, Duration: Slow to Fast