

ADJ COB CANNON LP200X - DMX TRAITS

5 CH	8-A CH	8-B CH	9 CH	10-A CH	10-B CH	12 CH	13 CH	16 CH	20 CH	DMX VALUES	FUNCTION
1	1		1	1	1	1	1	1	1		Red
										0 - 255	0 - 100%
				2					2		Red Fine
										0 - 255	Fine adjustment, 16-bit
2	2		2	3	2	2	2	2	3		Green
										0 - 255	0 - 100%
				4					4		Green Fine
										0 - 255	Fine adjustment, 16-bit
3	3		3	5	3	3	3	3	5		Blue
										0 - 255	0 - 100%
				6					6		Blue Fine
										0 - 255	Fine adjustment, 16-bit
4	4		4	7	4	4	4	4	7		Amber
										0 - 255	0 - 100%
				8					8		Amber Fine
										0 - 255	Fine adjustment, 16-bit
5	5		5	9	5	5	5	5	9		Lime
										0 - 255	0 - 100%
				10					10		Lime Fine
										0 - 255	Fine adjustment, 16-bit
		1			6	6	6	6	11		Color Macros
										0 - 255	See Color Macros Table
		2	6		7		7	7	12		Color Temperature
										0 - 255	2300K - 9900K Linear
	6	3	7		8	7	8	8	13		Shutter, Strobe
										0 - 31	LEDs Off
										32 - 63	LEDs On
										64 - 95	Strobe effect, slow to fast
										96 - 127	LEDs On
										128 - 159	Pulse effect in sequences
										160 - 191	LEDs On
										192 - 223	Random strobe effect, slow to fast
224 - 255	LEDs On										
	7	4	8		9	8	9	9	14		Dimmer
										0 - 255	Intensity, 0 to 100%
	8	5	9		10	9	10	10			Dimmer Fine
										0 - 255	Fine adjustment, 16-bit
						10		11	15		Auto Programs
										0 - 10	Off
										11 - 26	Auto Program 1
										27 - 43	Auto Program 2
										44 - 60	Auto Program 3
										61 - 76	Auto Program 4
										77 - 93	Auto Program 5
										94 - 110	Auto Program 6
111 - 126	Auto Program 7										
127 - 143	Auto Program 8										

ADJ COB CANNON LP200X - DMX TRAITS

5 CH	8-A CH	8-B CH	9 CH	10-A CH	10-B CH	12 CH	13 CH	16 CH	20 CH	DMX VALUES	FUNCTION
											Auto Programs (continued)
						10		11	15	144 - 160	Auto Program 9
										161 - 176	Auto Program 10
										177 - 193	Auto Program 11
										194 - 210	Auto Program 12
										211 - 226	Auto Program 13
										227 - 255	No Function
						11		12	16		Auto Programs Speed
										0 - 255	Slow to fast
						12		13	17		Auto Programs Fade
										0 - 255	Least to most
		6					11	14	18		Dim Mode
										0 - 20	Default to unit setting
										21 - 40	Standard
										41 - 60	Stage
										61 - 80	TV
										81 - 100	Architectural
										101 - 120	Theatre
										121 - 140	Stage 2
										141 - 160	Dim Speed, fast to slow (0.1s - 10s)
										161 - 255	Default to unit setting
		7					12	15	19		Dim Curves
										0 - 20	Square
										21 - 40	Linear
										41 - 60	Inv Squa
										61 - 80	S Curve
										81 - 255	No Function
		8					13	16	20		Refresh Rates
										0 - 15	Default to unit setting
										16 - 30	900 Hz
										31 - 45	1000 Hz
										46 - 60	1100 Hz
										61 - 75	1200 Hz
										76 - 90	1300 Hz
										91 - 105	1400 Hz
										106 - 120	1500 Hz
										121 - 135	2500 Hz
										136 - 150	4000 Hz
										151 - 165	5000 Hz
										166 - 180	10000 Hz
										181 - 195	15000 Hz
										196 - 210	20000 Hz
										211 - 225	25000 Hz
										226 - 255	No Function