

DMX TRAITS

CHANNEL					DMX VALUES	FUNCTION
1CH	2CH	3CH	7CH	9CH		
1						Fog and Random Color Change
					000 - 031	Off
					032 - 255	Max Fog and Random Color Change
	1	1	1	1		Fog
					000 - 031	Off
					032 - 255	Max Fog
	2	2			000 - 255	Color Macros , see Color Macros Chart section of this manual
			2	2	000 - 255	Red , 0% to 100%
			3	3	000 - 255	Green 1 (Outer LEDs) , 0% to 100%
			4	4	000 - 255	Blue , 0% to 100%
			5	5	000 - 255	Amber , 0% to 100%
			6	6	000 - 255	Green 2 (Inner LEDs) , 0% to 100%
			7	7	000 - 255	UV , 0% to 100%
		3		8		Strobing
					000 - 031	Off
					032 - 095	Strobing, slow to fast
					096 - 159	Pulse Effect
					160 - 255	Random Strobe, slow to fast
				9	000 - 255	Master Dimmer , 0% to 100%